



ブラシレスDCモーター

RB-3630-68

主な用途：
電動カーテン、ATM、自動販売機、パルプ



MODEL	VOLTAGE		NO LOAD		AT MAXIMUM EFFICIENCY						STALL	
	OPERATING RANGE	NOMINAL	SPEED	CURRENT	SPEED	CURRENT	TORQUE		OUTPUT	EFF	TORQUE	
			rpm	A	rpm	A	g.cm	mN-m	W	%	g.cm	mN-m
RB-3630-68-N-01	9.0V-14.0V	12.0V CONSTANT	2950	0.16	2251	0.52	136.9	13.42	3.2	51.1	578.4	56.71
RB-3630-68-N-02	19.0V-26.0V	24.0V CONSTANT	4680	0.13	3562	0.41	153	15	5.6	56.2	641.1	62.85
RB-3630-68-N-03	19.0V-26.0V	24.0V CONSTANT	11900	0.35	9065	1.08	170.8	16.75	15.9	61	700	68.63
RB-3630-68-N-04	5.8V-12.0V	6.0V CONSTANT	3000	0.35	2300	0.85	102	10	2.42	57.2	459	45

シャフト長、性能パラメータ、EMC対策は用途に応じて調整可能です。詳細は営業担当までお問い合わせください。

